










BRAVO 502

TOP LINE DISPLAY NUMERIC POCSAG PAGER

CommtechWireless

-  UP TO 18 PERSONAL MEMORY SLOTS
-  PROTECT UP TO 10 MESSAGES
-  INDIVIDUAL MESSAGE DELETE OR DELETE ALL
-  BACKLIGHT
-  PRIVATE TIME
-  TIME AND DATE DISPLAY
-  ALERT TYPES: MELODY, CHIRP, VIBRATE, VIBRATE-CHIRP, SILENT
-  BATTERY LOW INDICATOR AND ALERT
-  OUT-OF-RANGE INDICATOR AND ALERT



TOP MOUNT, UL-RATED NUMERIC PAGER

The Bravo 502 numeric pager is an intrinsically safe, top mount pager ideal for applications where ease-of-use and safety are important.

Easily read whilst still attached to the hip of the wearer, the Bravo 502 reduces the chance of the pager being misplaced, a critical issue during an emergency.

SELECTABLE ALERT TYPES

Providing a high level of flexibility to any communications solution, the Bravo 502 pager features five selectable alert tones. Along with the Melody tone setting, the Bravo 502 features Chirp, Vibrate, Vibrate and Chirp, and Silent.

UNREAD MESSAGE REMINDER

For those times when everything is moving at a mile a second, the Bravo 502 numeric pager features an unread message reminder - ensuring that you won't forget a message, even when you don't have the time to read it right away..

OUT-OF-RANGE INDICATOR AND ALERT

When a user takes a Bravo 502 pager out of the range of the communications system, the unit can be configured to sound an alert. This simple and efficient feature ensures that staff carrying pagers are aware when they are out of range.

GET THE MESSAGE

The Bravo 502 pager provides memory slots for up to 18 personal messages. In addition, users can protect a total of 10 messages from deletion.

When the pager memory is full, the Bravo 502 will alert the user - ensuring there is enough memory available for incoming messages.

CONTINUOUS MESSAGE INDICATOR

When an incoming message requires more than the available characters of a single message, its content will be broken into a continuous message of two or more screens. Where this occurs, the Bravo 502 alerts the user with a graphical continuous message symbol.

BRAVO 502

TOP LINE DISPLAY NUMERIC POCSAG PAGER



TECHNICAL SPECIFICATIONS

Bravo 502 POCSAG

Model No.	Br502	
Frequency	VHF (135-175MHz) UHF (452-468MHz) 900MHz (929-932MHz)	
Code Format	31/21 POCSAG Code	
Channel Spacing	25 kHz	
Frequency Deviation	+/- 4.5 kHz	
Paging Sensitivity	-107 dBm -104dBm	
EIA Selectivity	55 dB	40 dB
EIA Spurious and Image	50 dB	40 dB
IM Rejection	50 dB	40 dB
Operating Temperature	-10°C to 50°C	5°C to 40°C
Alert Tone Loudness	75 dB @ 12 inches	
Battery Type	1 x Alkaline AAA	
Battery Life	~70 Days	
Weight (with battery)	45 grams (2.29oz)	
Dimensions	64 (L) x 43 (W) x 19.5 (H) mm 2.5 (L) x 1.7 (W) x 0.8 (H) inches	



Product Name

Ordering Code



This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Authorised Distributor



www.commtechwireless.com
sales@commtechwireless.com

Australia
PO Box 1037
OPDC 6916
PERTH, Western Australia

Phone: +61 8 6240 0000
Fax: +61 8 6240 0001

United States
8301 Cypress Plaza Drive,
Suite 105
JACKSONVILLE, FL,
32256-4416

Phone: +1 904 281 0073
Fax: +1 904 281 0074